




## OMX 390LVDT

- Input for LVDT sensors
- Output 0/4...20mA/0...5mA/0...2/5/10V/±10V
- Teach-in, Digital filters, Tare, Mat. function, Linearization
- Quick configuration by DIP switch
- PC configurable via USB-C port
- Galvanic separation 2.5 kVAC
- Power supply 10...30 VDC/24 VAC

### Option

Data output

### DIGITAL ISOLATED TRANSMITTER



The OMX 390 model series are very fast DIN rail mountable digital transmitters with a Teach-in function.

Type OMX 390LVDT is a transmitter for LVDT sensor. Setting of both the input and output ranges can be done conveniently by a DIP switch located on the side of the housing or from a PC via the OM Link SW.

This device is based on a 32-bit processor, fast 24-bit  $\Delta\Sigma$  ADC with PGA and 16-bit DAC, which guarantees high accuracy and excellent stability.

### OPERATION

The device can be configured either by DIP switches located on the side of the housing or by PC using the OM Link SW. The same SW can be used to edit and archive all device settings, as well as to perform firmware updates and customer calibration.

Tech-in process can be performed for the measuring range currently selected using the front panel buttons.

All settings are stored in the EEPROM memory (preserved even after power-off).

### OPTION

**DATA OUTPUTS** are for their rate and accuracy suitable for transmission of the measured data for further projection or directly into the control systems. We offer an isolated RS485 with ASCII and Modbus protocol.

### STANDARD FUNCTIONS

#### PROGRAMMABLE INPUT

**Standard setting:** any display values can be assigned to Min and Max values of a defined standard input signal

**Teach-in:** any display values can be assigned to Min and Max values of actual (unknown) input signal

**Manual setting:** known Min and Max input signal values can be entered manually and any display values can be assigned to each signal

#### ANALOG OUTPUT

**Type:** isolated, programmable with a resolution of 16 bit, rate < 160  $\mu$ s

**Ranges:** 0...2/5/10 V/±10 V, 0...5 mA/0/4...20 mA

#### FUNCTIONS

**Linearization:** non-linear signal is converted by a 100-point linear interpolation

**Tare:** designed to reset display upon non-zero input signal

**Offset:** compensation for the difference between measured and actual/requir. value

**Math functions:** polynomial, inverse polynomial, logarithm, exponential, power, root

**Simulation:** test mode in which range, value and duration of the step can be set

#### DIGITAL FILTERS

**Floating / Exponential / Arithmetic average:** from 2 to 100 measurements

**Rounding:** setting a „shorter” number for further signal processing

#### EXTERNAL CONTROL

**Hold:** display/instrument blocking

**Lock:** control keys blocking

**Tare:** activation and tare resetting

**Hold Min/Max/Max-Min/AVG:** triggering the measurement for Min/Max/AVG value

**Cumulative measurement:** series of measurements with their total sum

**Sample:** start of a one-time measurement

## TECHNICAL DATA

### INPUT

|  |  |
|--|--|
| No. of inputs                                  | 1  |
| The range is adjustable in the instrument menu |  |
| <b>LVDT</b> Sensor power supply                | 1, 3, or 5 VAC with a frequency of 2.5, 5, or 10 kHz |
| Amplification                                  | 1, 2, 4 or 8   |

### EXTERNAL INPUT

|               |   |
|---------------|---|
| No. of inputs | 2, on contact   |
| Function      | No function assigned<br>Activation of Tare<br>Reset of Tare<br>Tare activation (<1s) + Zero tare (>1s)<br>Activation of Tech-In for Offset<br>Controlling of cumulative measurement<br>Measurement paused<br>Take a one-off measurement<br>Value of minimum *<br>Value of maximum *<br>Value of MAX-MIN*<br>Hold - Average value*<br>Device buttons blocked |
|               |   |
|               |   |
|               |   |

\*The value is calculated from the period since the previous activation of the ext. input.

### INSTRUMENT SPECIFICATION

|                 |   |
|-----------------|---|
| TC              | 15 ppm/°C   |
| Accuracy        | ±0.1% of FS   |
| Rate            | 1...100 measurements/s  |
| Latency         | < 580 µs  |
| Overload        | 10x (t < 30 ms), 2x   |
| Functions       | Teach-in, tare, offset, math. functions, delayed start, simulation                              |
| Digital filters | exponential / floating / arithmetic average, rounding setup only via OM Link                    |
| Math functions  | polynomial / inverse polynomial / logarithm / exponential / power / root setup only via OM Link |
| Linearization   | linear interpolation in 100 points setup only via OM Link                                       |
| OM Link         | company communication interface for operation, setting and update of instruments (USB-C)        |
| Watch-dog       | reset after 500 ms  |
| Calibration     | at 25°C and 40 % rh.  |

### ANALOG OUTPUT

|                |   |
|----------------|---|
| No. of outputs | 1   |
| Type           | isolated, adjustable with 16-bit DAC, output type and range is selectable |
| TC             | 15 ppm/°C   |
| Accuracy       | ±0.02% of FS<br>±0.03% of FS<br>±0.06% of FS                              |
| Rate           | response to change of value < 160 µs                                      |

|           |          |                       |
|-----------|----------|-----------------------|
| Ranges    | Range    | Error indication      |
| 0...2 V   | -2.2 V   | resistive load > 1 kΩ |
| 0...5 V   | -5.5 V   | resistive load > 1 kΩ |
| 0...10 V  | -11.0 V  | resistive load > 1 kΩ |
| ±10 V     | -11.0 V  | resistive load > 1 kΩ |
| 0...5 mA  | -5.5 mA  | comp. < 600 Ω/12 V    |
| 0...20 mA | -22.0 mA | comp. < 600 Ω/12 V    |
| 4...20 mA | -3.2 mA  | comp. < 600 Ω/12 V    |

|                                   |   |
|-----------------------------------|---|
| Indication of broken current loop | Indication of broken current loop   |
| Error indication                  | one or more error conditions can be selected from a predefined list in the OM Link software according to user requirements. |

### DATA OUTPUTS

|                  |   |
|------------------|---|
| No. of outputs   | 1   |
| Type             | RS 485, isolated 10/100BaseT  |
| Protocol         | Modbus RTU<br>Modbus TCP/IP (Slave)   |
| Rate             | 600...230 400 Baud<br>100 Mbit/s  |
| Data format      | Format: 8bits + parity + stop bit<br>Parity: none / even / odd<br>Stop bit: 1/1.5/2 |
| Addressing       | 1...247 instruments   |
| Line termination | by internal resistance 120 Ω<br>wire jumper on the connector of the last device     |

### POWER SUPPLY

|             |  |
|-------------|--|
| Range       | 10...30 VDC / 24 AC, ±10 %, PF ≥ 0.4, $I_{B1} \leq 40$ A / 1 ms, isolated Protection by fuse inside the device |
| Consumption | < 3.4 W / 3.3 VA<br>< 5.0 W / 4.9 VA (at 80 Ω load)  |

### MECHANIC PROPERTIES

|              |                                     |
|--------------|-------------------------------------|
| Material     | PA66, incombustible UL 94 V-0, blue |
| Dimensions   | 25 x 79 x 90.5 mm (w x h x d)       |
| Installation | to DIN rail 35 mm wide              |

### OPERATING CONDITIONS

|                       |  |
|-----------------------|--|
| Connection            | connector terminal blocks, section < 1.5 mm²   |
| Stabilization period  | within 5 minutes after switch-on   |
| Working temperat.     | -20°...60°C  |
| Storage temperat.     | -20°...85°C  |
| Working humidity      | < 95 % r.v., non condensing  |
| Protection            | IP20   |
| Construction          | safety class I   |
| El. safety            | EN 61010-1, A2   |
| Dielectric strength   | 2.5 kVAC for 1 min test between supply and input<br>2.5 kVAC for 1 min test between input and outputs                |
| Insulation resist.*   | for pollution degree II, measurement cat. III<br>power supply > 300 V (Pi), 255 V (Di)<br>Input/outputs > 300 V (Pi) |
| EMC                   | EN 61326-1:2021, Industrial area   |
| RoHS                  | EN IEC 63000-2018  |
| Seismic qualification | IEC/IEEE 60980-344 Edition 1.0, 2020, par. 6, 9  |
| Mechanical resistance | EN 60068-2-6 ed. 2:2008  |

\* PI - Primary insulation, DI - Double insulation

## CONNECTION

## ORDER CODE

**OMX 390LVDT**

-  -

Output

Analog  
Data - RS 485  
Data - TCP/IP Modbus

1


2

3

00

Specification

customized version, do not fill in



Basic configuration of the instrument is indicated in bold.